



# Release 185 Graphics Drivers ***Release Notes***

**Version 185.81**

**For Windows Vista 32-bit  
and Windows Vista 64-bit**

---

**NVIDIA Corporation  
April 30, 2009**

Published by  
NVIDIA Corporation  
2701 San Tomas Expressway  
Santa Clara, CA 95050

## **Notice**

ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE.

Information furnished is believed to be accurate and reliable. However, NVIDIA Corporation assumes no responsibility for the consequences of use of such information or for any infringement of patents or other rights of third parties that may result from its use. No license is granted by implication or otherwise under any patent or patent rights of NVIDIA Corporation. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. NVIDIA Corporation products are not authorized for use as critical components in life support devices or systems without express written approval of NVIDIA Corporation.

## **Trademarks**

NVIDIA, the NVIDIA logo, 3DFX, 3DFX INTERACTIVE, the 3dfx Logo, STB, STB Systems and Design, the STB Logo, the StarBox Logo, NVIDIA nForce, GeForce, NVIDIA Quadro, NVDVD, NVIDIA Personal Cinema, NVIDIA Soundstorm, Vanta, TNT2, TNT, RIVA, RIVA TNT, VOODOO, VOODOO GRAPHICS, WAVEBAY, Accuviv Antialiasing, the Audio & Nth Superscript Design Logo, CineFX, the Communications & Nth Superscript Design Logo, Detonator, Digital Vibrance Control, DualNet, FlowFX, ForceWare, GIGADUDE, Glide, GOFORCE, the Graphics & Nth Superscript Design Logo, Intellisample, M-BUFFER, nfiniteFX, NV, NVChess, nView, NVKeystone, NVOptimizer, NVPinball, NVRotate, NVSensor, NVSync, the Platform & Nth Superscript Design Logo, PowerMizer, Quincunx Antialiasing, Sceneshare, See What You've Been Missing, StreamThru, SuperStability, T-BUFFER, The Way It's Meant to be Played Logo, TwinBank, TwinView and the Video & Nth Superscript Design Logo are registered trademarks or trademarks of NVIDIA Corporation in the United States and/or other countries. Other company and product names may be trademarks or registered trademarks of the respective owners with which they are associated.

Intel, Indeo, and Pentium are registered trademarks of Intel Corporation. Microsoft, Windows, Windows NT, Windows Vista, Direct3D, DirectDraw, and DirectX are trademarks or registered trademarks of Microsoft Corporation. OpenGL is a registered trademark of Silicon Graphics Inc. PCI Express, PCI-SIG, and the PCI-SIG design marks are registered trademarks and/or service marks of PCI-SIG. DisplayPort is a trademark of the Video Electronics Standards Association (VESA).

Other company and product names may be trademarks or registered trademarks of the respective owners with which they are associated.

## **Copyright**

© 2008, 2009 by NVIDIA Corporation. All rights reserved.



# Table of Contents



## 1. Introduction to *Release Notes*

Structure of the Document . . . . .	1
Changes in this Edition . . . . .	1

## 2. Release 185 Driver Changes

Version 185.81 Highlights . . . . .	3
What's New in Release 185 . . . . .	3
What's New in Version 185.81 . . . . .	5
Limitations in This Release. . . . .	5
Changes in Version 185.81 . . . . .	6
Fixed Issues—Windows Vista 32-bit . . . . .	6
Fixed Issues—Windows Vista 64-bit . . . . .	6
Open Issues in Version 185.81 . . . . .	7
Windows Vista 32-bit Issues . . . . .	7
Windows Vista 64-bit Issues . . . . .	8
Not NVIDIA Issues . . . . .	9
Windows Vista Limitations . . . . .	9
Unsupported Features . . . . .	10
OpenGL Application Issues . . . . .	11
Application Issues . . . . .	12
Known Product Limitations . . . . .	13
Image Sharpening Control not Available with GeForce 8 Series and later GPUs . . . . .	13
Gigabyte GA-6BX Motherboard . . . . .	13

## 3. The Release 185 Driver

Hardware and Software Support . . . . .	15
Supported Operating Systems . . . . .	15
Supported NVIDIA Products . . . . .	16
Supported Languages . . . . .	18
Driver Installation . . . . .	20
Minimum Hard Disk Space . . . . .	20
Before You Begin. . . . .	20
Installation Instructions. . . . .	20

## A. Mode Support for Windows

General Mode Support Information . . . . .	22
Default Modes Supported by GPU . . . . .	23
Understanding the Mode Format. . . . .	23
GeForce 9M, 8M, 100M, 200M and Quadro NVS and Quadro FX Notebook GPUs . . . . .	24
Modes Supported by TV Encoders . . . . .	27



# List of Tables



<b>Table 3.1</b>	Supported NVIDIA GeForce GPUs . . . . .	16
<b>Table 3.2</b>	Supported NVIDIA Quadro NVS GPUs. . . . .	17
<b>Table 3.3</b>	Supported NVIDIA Quadro NVS GPUs. . . . .	18
<b>Table A.1</b>	Modes Supported for High Resolution Displays . . . . .	22
<b>Table A.2</b>	Non-standard Modes Supported . . . . .	22
<b>Table A.3</b>	Mode Support for S-Video and Composite Out . . . . .	27
<b>Table A.4</b>	Mode Support for Component YPrPb Out and DVI Out . . . . .	27

## CHAPTER

## 1

# INTRODUCTION TO *RELEASE NOTES*

This edition of *Release Notes* describes the Release 185 Graphics Drivers for Microsoft® Windows® Vista. NVIDIA provides these notes to describe performance improvements and bug fixes in each documented version of the driver.

**This is a reference driver that can be installed on supported NVIDIA GeForce, Quadro NVS, and Quadro FX notebook GPUs.** However, please note that your notebook original equipment manufacturer (OEM) provides certified drivers for your specific notebook on their website. NVIDIA recommends that you check with your notebook OEM about recommended software updates for your notebook. OEMs may not provide technical support for issues that arise from the use of this driver.

## Structure of the Document

---

This document is organized in the following sections:

- [“Release 185 Driver Changes” on page 2](#) gives a summary of changes, and fixed and open issues in this version.
- [“The Release 185 Driver” on page 15](#) describes the NVIDIA products and languages supported by this driver, the system requirements, and how to install the driver.
- [“Mode Support for Windows” on page 21](#) lists the default resolutions supported by the driver.

## Changes in this Edition

---

This edition of the *Release Notes* for Windows Vista includes information about NVIDIA graphics driver version 185.81, and lists changes made to the driver since version 179.48. These changes are discussed beginning with the chapter [“Release 185 Driver Changes” on page 2](#).

## CHAPTER

## 2

# RELEASE 185 DRIVER CHANGES

This chapter describes open issues for version 185.81, and resolved issues and driver enhancements for versions of the Release 185 driver up to version 185.81. The chapter contains these sections:

- “Version 185.81 Highlights” on page 3
- “Changes in Version 185.81” on page 6
- “Open Issues in Version 185.81” on page 7
- “Not NVIDIA Issues” on page 9
- “Known Product Limitations” on page 13

## Version 185.81 Highlights

---

This section provides highlights of version 185.81 of the NVIDIA Release 185 Driver for Windows Vista.

- [What's New in Release 185](#)
- [What's New in Version 185.81](#)
- [Limitations in This Release](#)

### What's New in Release 185

---

- This is a reference driver for Quadro FX, Quadro NVS series, GeForce 8M, 9M, 100M, and 200M series notebook GPUs.

Some notebooks are not supported by this release. Refer to the [“Supported NVIDIA Products” on page 16](#) for the list of supported GPUs and notebooks.

### NVIDIA Control Panel Updates

#### 3D Settings

- **Ambient Occlusion** setting (*new* in the Manage 3D Settings page for Windows Vista)

Ambient occlusion enhances depth perception and adds realism to 3D scenes by providing a soft shadow effect to objects based on their placement in the scene.

- **SLI Antialiasing** (*new* in the Manage 3D Settings page for Windows Vista)

Now available under Windows Vista as well as Windows XP.

- **Workstation/Quad-buffered 3D Stereo** (*new* Stereo-Display mode settings in the Manage 3D Settings page)

Added support for the following stereoscopic 3D hardware and modes:

- GeForce 3D Vision hardware—generic active stereo, via on-board DIN connector, passive (Clone mode) modes, and 3D DLP display
- Generic active stereo
- Horizontal interlaced stereo displays
- Sub-field stereo displays
- Side-field stereo displays
- SeeFront Autostereoscopic LCD
- Texas Instruments 3D Ready DLP® (Digital Light Processing technology) displays
- Tridality Multi-View and Single-Viewer displays

- Planar StereoMirror™ displays

## Display

- **Set up Multiple Displays** (*revised* under Windows Vista)

In Release 185, when SLI mode is enabled, users can now select a display from different GPUs as long as the GPUs are in the same SLI group.

- Displays must still be connected to the same GPU under Clone mode.
- Quad SLI: When using GeForce X2, Quadro X2, or the GeForce GTX 295 graphics cards, only GPUs that have two display connectors can be used to drive displays. Typically, display connectors lined up on the same slot position are connected to the same GPU.
- NVIDIA recommends connecting displays to the same GPU to shorten the driver reload time on the initial setup.
- **Adjust Desktop Color Settings** page (*revised* under Windows Vista)  
Applications now have the option of controlling the desktop color settings.

## Video & Television

- **HDCP Status**

*New* page for verifying whether the system is HDCP-capable

- **Adjust TV Color Settings** page (*revised* under Windows Vista)

Applications now have the option of controlling the TV color settings.

## Display Driver Updates

### Device Support

Added support for EDID-like devices.

### Hotplug Behavior

When hotplugging or hot-unplugging a digital display, the driver detects the display and then configures the multi-display mode and display resolution based on the recent record of the displays connected. If no record exists, then the driver applies default settings. A popup message appears at the system notification tray to alert the user of the change.

The automatic display configuration also occurs upon powering on the computer and booting into Windows Vista if the driver detects a change in display connections since the last Windows session.

## Notebook-Specific Updates

NVIDIA Display Power Saving technology option appears in the Windows Vista Power Options->Advanced settings tab .



## Video Updates

- Compute-based DVD upscaling
- CUDA Video Encoder 1.1: Added support for CUDA-enabled GPUs with less than 32 cores to the NVIDIA Video Encoding library.

## CUDA Updates

- CUDA 2.2
- CUDA Video Encoder V1.1: Added support for CUDA-enabled GPUs with less than 32 cores to the NVIDIA Video Encoding library.

## OpenGL Updates

- Support for OpenGL 3.0
- Implemented NVX\_shader\_buffer\_load (OpenGL Shading Language).

## What's New in Version 185.81

---

- Supports NVIDIA PhysX hardware acceleration on GeForce 8M and 9M GPUs with a minimum of 256MB dedicated graphics memory (this driver package installs NVIDIA PhysX System Software v9.09.0203).
- See [“Changes in Version 185.81” on page 6](#) for a list of resolved issues.

## Limitations in This Release

---

The following are features that are not currently supported or have limited support in this driver release:

### **NVIDIA Control Panel features that are Not Yet Available**

Support for the following control panel features is under development and not yet available under Windows Vista:

- **Display Category**
  - The Graph tab on the Adjust Desktop Color Settings page is not available.

## Changes in Version 185.81

---

The following sections list the changes made and issues resolved since driver version 179.48.

The NVIDIA bug number and driver module are provided for reference.

### Fixed Issues—Windows Vista 32-bit

---

#### Single- GPU Issues

- GeForce 9500M/9400M: The multi-display mode switches from Dualview to single-display mode after changing the resolution and scaling option for the secondary display. [510300]

#### Multi- GPU Issues

- [SLI], GeForce8800M GTX: Bioshock—the game hangs with a blank screen when toggling to the full-screen mode using Alt+Tab at 1920x1200. [486274]

### Fixed Issues—Windows Vista 64-bit

---

#### Single- GPU Issues

- GeForce 8800M GTX: With HDTV connected to component-out and enabled in single-display mode, the display switches to the LVDS upon resume from Sleep or Hibernate mode. [457620]

## Open Issues in Version 185.81

---

As with every released driver, version 185.81 of the Release 185 driver has open issues and enhancement requests associated with it. This section includes lists of issues that are either not fixed or not implemented in this version. Some problems listed may not have been thoroughly investigated and, in fact, may not be NVIDIA issues. Others may have workaround solutions. *Many of these issues are system-specific and may not be seen on your particular notebook.*

- [“Windows Vista 32-bit Issues”](#) on page 7
- [“Windows Vista 64-bit Issues”](#) on page 8

### Windows Vista 32-bit Issues

---

#### Single GPU Issues

- Company of Heroes DirectX 10– scrolling the camera side to side causes hitching despite a high frame rate when stationary. [538673]

#### Quadro FX Series

- Quadro FX 3700M: When resuming from lid-close activated Sleep mode, keyboard and mouse response is very sluggish. [521241]
- Quadro FX 2700M: The NVIDIA Control Panel shows an extra display on the “Set up multiple displays” page. [540993]

#### GeForce 9M Series

- GeForce 9700M GTS: The system does not resume from Standby/Sleep mode. [542034]
- GeForce 9600M GT: The shortcut keys for selecting the color option in the NVIDIA Control Panel 'Adjust video color setting' page do not work. [515450]
- GeForce 9600M GT: With Clone mode enabled and the LVDS set to “Do not scale”, the LVDS resolution cannot be changed. [469380]
- GeForce 9600M GT: Hot keys (keyboard shortcut) for selecting the 'color' option in the 'Adjust video color setting' page do not work. [515450]
- GeForce 9400M G: The settings on the “Change Flat Panel Scaling” page are not updated properly after resizing the desktop and then restoring the default settings. [510854]
- GeForce 9400M G: Under Clone mode, each display has different video color settings from the NVIDIA Control Panel “Adjust Video Color Settings” page. [505275]

#### GeForce 8M Series

- GeForce 8800M GTX: External HDMI TV cannot be set to single-display mode, and cannot be set as the primary Clone mode or Dualview mode display. [470434]

- GeForce 8700M GT: VGA hotplug/unplug is not detected without refreshing the NVIDIA Control Panel or the Device Manager. [461613]
- GeForce 8600M GS: When a display is connected via component-out and Clone mode is enabled, the system switches to Dualview mode upon resume from Hibernate [490576]
- GeForce 8600M GT: MPEG1 and MPEG2 playback using iTunes is choppy. [537550]

## Multi-GPU Issues

- [SLI], GeForce 8800M GTX: The PhysX option is disabled by default after driver installation. [544945]
- [SLI], GeForce 8800M GTX: Far Cry 2 (DirectX 10)–sky textures show flickering corruption when changing the in-game resolution during gameplay. [492934]
- [SLI], GeForce 8800M GTX: The display list on the Set SLI Configuration page is not updated properly when hot-plugging or hot-unplugging a display. [478691]
- [SLI], GeForce 8700M GT: SLI display resolution is not restored after disabling SLI mode, changing the resolution under Clone mode, and then re-enabling SLI mode. [462251]
- [SLI], GeForce 8700M GT: When enabling SLI mode, changing the display to view SLI rendered content on does not work. [492292]

## Windows Vista 64-bit Issues

---

### Single GPU Issues

- GeForce 9600M GT: The shortcut keys for selecting the color option in the NVIDIA Control Panel 'Adjust video color setting' page do not work. [515450]
- GeForce 9400M G: The settings on the “Change Flat Panel Scaling” page are not updated properly after resizing the desktop and then restoring the default settings. [510854]

### Multi-GPU Issues

- [SLI], GeForce 8800M GTX: Multi-display mode is not preserved between users after performing a Fast User Switch. [541252]

## Not NVIDIA Issues

---

This section lists issues that are not due to the NVIDIA driver as well as features that are not meant to be supported by the NVIDIA driver for Windows Vista.

- “Windows Vista Limitations” on page 9
- “Unsupported Features” on page 10
- “OpenGL Application Issues” on page 11
- “Application Issues” on page 12

## Windows Vista Limitations

---

These are behaviors that may be different from Windows XP and are related directly to the Windows Vista operating system.

- **NVIDIA TurboCache**

Windows Vista now controls the allocation of system memory to the GPU for TurboCache functions. The Windows Vista Display Properties pages show the shared system memory (SSM), or how much memory is allocated for NVIDIA GPUs to use for TurboCache.

For more information on graphics memory reporting under Windows Vista, visit <http://www.microsoft.com/whdc/device/display/graphicsmemory.mspx>.

## Unsupported Features

---

The following are features and functionality that were available in driver releases supporting Windows XP, but are not—and will not be—available in driver releases for Windows Vista:

- **High resolution scaling desktop (HRSD)**
- **MultiView Display Mode** (for NVIDIA Quadro NVS graphics cards)
- **NVKeystone**
- **Unified back buffer (UBB) controls**
- **OpenGL Video Overlays**

This is an operating system limitation.

Vista window manager features will provide new ways of accomplishing overlays, but will require application porting.

- **Overclocking**

GPU overclocking is no longer supported in the default GPU driver control panel. This feature is available in the NVIDIA System Tools software, which you can download from [NVIDIA.com](http://NVIDIA.com).

- **GPU Temperature Monitoring**

Temperature monitoring is no longer supported in the default GPU driver control panel. This feature is available in the NVIDIA System Tools software, which you can download from [NVIDIA.com](http://NVIDIA.com).

- **AGP Settings Adjustment**

- **Video Zoom**

- **Pan & Scan** - the process of panning across the desktop in order to display a desktop on a monitor with lower resolution

- **Per-display Desktop Color Setting Adjustments**

For Clone mode, the desktop color setting adjustments through the NVIDIA Control Panel can only be made across all displays in a system, and not on a per-display basis.

- **Per-display Video Color Setting Adjustments**

For Dualview mode, the video color setting adjustments through the NVIDIA Control Panel can only be made across all displays in a system, and not on a per-display basis.

- **Edge Blending**
- **Run display optimization wizard**
- **Run multiple display wizard**

- **Run television setup wizard**
- **nView Horizontal and Vertical Span Modes**

Due to architectural changes in the new Windows Vista Window Display Driver Model (WDDM), span mode cannot be supported in NVIDIA graphics drivers. NVIDIA recommends using the built-in Windows Vista multi-display modes.

- **Display/Connection Wizard** (such as was provided with Windows Media Center Edition)
- **DVD/MPEG Extensions** (such as was provided with Windows Media Center Edition)
- **Audio Extensions** (such as was provided with Windows Media Center Edition)
- **NVIDIA nView Desktop Manager**

The nView Desktop Manager will not be included in drivers for GeForce products.

## OpenGL Application Issues

---

The following are known compatibility issues for OpenGL applications developed under Windows XP:

- Mixed GDI and OpenGL rendering does not work.

A number of applications use GDI to render UI components and object highlighting. This is not supported in the Windows Vista driver model.

NVIDIA recommends converting GDI rendering to OpenGL.

The following are some applications that are known to have this issue:

- Maya 7.01
- OneSpace Designer Modeling
- Applications, Tools, and Benchmarks not Supported Under Windows Vista
  - GLperf
  - 3ds max 8 (later releases may be supported)
  - CATIA V5R15 (V5R16 is supported)
  - PTC's CDRS 2001
- Front buffered rendering may be slow, especially when DWM is enabled.

Flushing the rendering queue while rendering to the front buffer may cause the window manager to recomposite. Applications should therefore minimize the frequency with which they flush the rendering queue.

## Application Issues

---

- GeForce 8600M GT: Warmonger 2.1—the game intermittently stops responding after changing in-game resolution. [482889]
- GeForce 8600M GT: Dead Space - a “your graphics card does not meet Dead Space minimum requirement” error message appears after launching the game. [491410]

*This is a limitation of the application, and only occurs if your monitor does not support 60 Hz refresh rate.*



## Known Product Limitations

---

This section describes problems that will not be fixed. Usually, the source of the problem is beyond the control of NVIDIA. Following is the list of problems and where they are discussed in this document:

- “Image Sharpening Control not Available with GeForce 8 Series and later GPUs” on page 13
- “Gigabyte GA-6BX Motherboard” on page 13

### Image Sharpening Control not Available with GeForce 8 Series and later GPUs

---

With GeForce 8 Series and later graphics cards, the **Image sharpening** slider on the NVIDIA Control Panel-> Display->Adjust Desktop Color Settings page is grayed out.

This control is intentionally disabled because image sharpening is not supported on GeForce 8 series and later GPUs.

### Gigabyte GA-6BX Motherboard

---

This motherboard uses a Linfinity regulator on the 3.3-V rail that is rated to only 5 A—less than the AGP specification, which requires 6 A. When diagnostics or applications are running, the temperature of the regulator rises, causing the voltage to the NVIDIA chip to drop as low as 2.2 V. Under these circumstances, the regulator cannot supply the current on the 3.3-V rail that the NVIDIA chip requires.

This problem does not occur when the graphics board has a switching regulator or when an external power supply is connected to the 3.3-V rail.



## CHAPTER

## 3

# THE RELEASE 185 DRIVER

This chapter covers the following main topics:

- “Hardware and Software Support” on page 15
- “Driver Installation” on page 20

## Hardware and Software Support

---

### Supported Operating Systems

---

The Release 185 driver, version 185.81, has been tested with Microsoft Windows® Vista RTM OS builds version 6000 or higher, and supports both 32-bit and 64-bit versions of Windows Vista Editions:

- Windows Vista Home Basic
- Windows Vista Home Premium
- Windows Vista Business
- Windows Vista Enterprise Edition
- Windows Vista Ultimate

## Supported NVIDIA Products

---

- “Supported GeForce GPUs” on page 16
- “Supported NVIDIA Quadro NVS GPUs” on page 17
- “Supported NVIDIA Quadro FX GPUs” on page 18

## Supported GeForce GPUs

Table 3.1 lists the NVIDIA products supported by the Release 185 driver, version 185.81

**Table 3.1** Supported NVIDIA GeForce GPUs

### Consumer Products

GeForce GTX 280M  
 GeForce GTX 260M  
 GeForce GTS 160M  
 GeForce GT 130M  
 GeForce GT 120M  
 GeForce G 102M  
 GeForce G 110M  
 GeForce G 107M  
 GeForce G 105M  
 GeForce G 103M  
 GeForce 9800M GTX  
 GeForce 9800M GTS  
 GeForce 9800M GT  
 GeForce 9800M GS  
 GeForce 9700M GTS  
 GeForce 9700M GT  
 GeForce 9650M GT  
 GeForce 9650M GS  
 GeForce 9600M GT  
 GeForce 9600M GS  
 GeForce 9500M GS  
 GeForce 9500M G  
 GeForce 9400M G  
 GeForce 9400M  
 GeForce 9300M GS  
 GeForce 9300M G  
 GeForce 9200M GS  
 GeForce 9200M GE  
 GeForce 9100M G  
 GeForce 8800M GTX  
 GeForce 8800M GTS  
 GeForce 8800M GS  
 GeForce 8700M GT

**Table 3.1** Supported NVIDIA GeForce GPUs**Consumer Products**

GeForce 8600M GT  
GeForce 8600M GS  
GeForce 8400M GT  
GeForce 8400M GS  
GeForce 8400M G  
GeForce 8200M G

---

The driver supports notebooks based on the GPUs listed in [Table 3.1](#). However, the following notebooks are *not* supported in this release:

- Hybrid SLI notebooks:
  - Acer Aspire 7530
  - BenQ Joybook S42
  - Fujitsu Siemens Amilo Xi 3650
  - MSI EX630
  - Qosmio X305-Q706
  - Qosmio X305-Q708
- **Fujitsu** notebooks (please contact the notebook OEM for driver support for these notebooks)
- **Lenovo ThinkPad** notebooks (please contact the notebook OEM for driver support for these notebooks)
- **Sony VAIO** notebooks (please contact the notebook OEM for driver support for these notebooks)
- Any notebook that is launched after the release of this driver version.

**Supported NVIDIA Quadro NVS GPUs**

[Table 3.2](#) lists the NVIDIA products supported by the Release 185 driver, version 185.81

**Table 3.2** Supported NVIDIA Quadro NVS GPUs**Consumer Products**

Quadro NVS 320  
Quadro NVS 160M  
Quadro NVS 150M  
Quadro NVS 140M

**Table 3.2** Supported NVIDIA Quadro NVS GPUs**Consumer Products**

Quadro NVS 135M  
 Quadro NVS 130M

---

The driver supports notebooks based on the GPUs listed in [Table 3.2](#). However, the following notebooks are *not* supported in this release:

- **Lenovo ThinkPad** notebooks (please contact the notebook OEM for driver support for these notebooks)
- Any notebook that is launched after the release of this driver version.

**Supported NVIDIA Quadro FX GPUs**

[Table 3.3](#) lists the NVIDIA products supported by the Release 185 driver, version 185.81

**Table 3.3** Supported NVIDIA Quadro NVS GPUs**Consumer Products**

Quadro FX 3700M  
 Quadro FX 3600M  
 Quadro FX 2700M  
 Quadro FX 1700M  
 Quadro FX 1600M  
 Quadro FX 770M  
 Quadro FX 570M  
 Quadro FX 370M  
 Quadro FX 360M

---

**Supported Languages**

The Release 185 Graphics Drivers supports the following languages in the main driver Control Panel:

English (USA)	German	Portuguese (Euro/Iberian)
English (UK)	Greek	Russian
Arabic	Hebrew	Slovak
Chinese (Simplified)	Hungarian	Slovenian
Chinese (Traditional)	Italian	Spanish
Czech	Japanese	Spanish (Latin America)
Danish	Korean	Swedish
Dutch	Norwegian	Thai

Finnish  
French

Polish  
Portuguese (Brazil)

Turkish

# Driver Installation

---

## Minimum Hard Disk Space

---

The hard disk space requirement is minimum 200 MB.

## Before You Begin

---

- If you have previously installed NVIDIA nTune, NVIDIA recommends that you uninstall nTune before installing this driver. After the driver install is complete, you can reinstall NVIDIA nTune.
- Check to make sure that your notebook has a supported GPU and is not listed in the exclusion list (see “[Supported NVIDIA Products](#)” on page 16).
- It is recommended that you back up your current system configuration.
- If you own a Dell Inspiron 1420, Dell XPS M1330, or Dell XPS M1530, Dell LatitudeD630 or D630c, it is highly recommended that you first install this [Dell software update](#).

## Installation Instructions

---

- 1 Follow the instructions on the NVIDIA .com Web site driver download page to locate the appropriate driver to download, based on your hardware and operating system.
- 2 Click the driver download link.
- 3 The license agreement dialog box appears.
- 4 Click **Accept** if you accept the terms of the agreement, then either open the file or save the file to your PC and open it later.
- 5 Extract the zip files to a temporary folder on your PC.
- 6 Open the NVIDIA driver installation .EXE file to launch the NVIDIA InstallShield Wizard.
- 7 Follow the instructions in the NVIDIA InstallShield Wizard to complete the installation.

**Note:** After the driver installation, Windows may default to 16-bpp color and disable the Desktop Window Manager (DWM). To work around this issue, set the color to 32-bpp and then reboot the PC.



## APPENDIX



## MODE SUPPORT FOR WINDOWS

This chapter details the Windows modes supported by the Release 185 driver for NVIDIA products. It contains these sections:

- “General Mode Support Information” on page 22
- “Default Modes Supported by GPU” on page 23
- “Modes Supported by TV Encoders” on page 27

## General Mode Support Information

---

The NVIDIA graphics driver includes a standard list of display modes that are supported by default. These modes are listed in the section [“Default Modes Supported by GPU”](#) on page 23.

The actual modes available depend on the capabilities of the display. In addition, the NVIDIA graphics driver has a “dynamic EDID detection” capability and will make available *additional* modes that are listed in the display EDID, provided the graphics hardware can support it.

The NVIDIA graphics driver also supports the high resolutions available with the displays listed in [Table A.1](#) as well as the non-standard modes listed in [Table A.2](#).

**Table A.1** Modes Supported for High Resolution Displays

Display	Maximum Resolution	Hardware Requirements
Apple 30" Cinema HD Display (Dual link DVI)	2560x1600 @ 60 Hz	<ul style="list-style-type: none"> <li>• All GeForce 7 series GPUs and later</li> <li>• GeForce 6800 Ultra 512</li> <li>• GeForce 6800 with 512 MB</li> </ul>
Dell WFP 3007 (Dual Link DVI)	2560x1600 @ 60 Hz	
HP LP3065 dual-link DVI flat panel	2560x1600 @ 60Hz.	

**Table A.2** Non-standard Modes Supported

Resolution
1680 x 1050
1366 x 768

## Default Modes Supported by GPU

---

This section lists the modes that are included by default in the driver INF for the following product families:

- “GeForce 9M, 8M, 100M, 200M and Quadro NVS and Quadro FX Notebook GPUs” on page 24

## Understanding the Mode Format

---

Figure A.1 gives an example of how to read the mode information presented in this section.

Resolution	Color Depth	Refresh Rates
-----	-----	-----
1024 x 768	32 60 70 72 75 85 100 120 140 144 150 170 200	

**Example entry:** 1024 x 768 32 60 70 72 75 85 100 120 140 144 150 170 200

**Meaning:**

Resolution:	1024 x 768
Color depth:	32 bpp
Refresh rates:	60 Hz, 70 Hz, 72 Hz, 75 Hz, 85 Hz, 100 Hz, 120 Hz, 140 Hz, 144 Hz, 150 Hz, 170 Hz, and 200 Hz

**Figure A.1** Mode Format

**Note:**

- Horizontal spanning modes of 3840x1080 and above, and vertical spanning modes of 1920x2160 and above generally require at least 32 MB of video memory at 32 bpp.
- An “i” next to the refresh rate indicates an interlaced refresh rate.

## GeForce 9M, 8M, 100M, 200M and Quadro NVS and Quadro FX Notebook GPUs

---

This sections lists the supported display resolutions, color depths, and refresh rates for the products listed in [Table 3.1](#), [Table 3.2](#), and [Table 3.3](#).

### Standard Modes

640 x 480	8	60 70 72 75 85 100 120 140 144 150 170 200 240
800 x 600	8	60 70 72 75 85 100 120 140 144 150 170 200 240
848 x 480	8	60 70 72 75 85 100 120 140 144 150 170 200 240
960 x 600	8	60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	8	60 70 72 75 85 100 120 140 144 150 170 200 240
1088 x 612	8	60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	8	60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	8	60
1280 x 768	8	60 70 72 75 85 100 120 140 144 150 170
1280 x 800	8	60 70 72 75 85 100 120 140 144 150 170
1280 x 960	8	60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	8	60 70 72 75 85 100 120 140 144 150 170
1360 x 768	8	60 70 72 75 85 100 120 140 144 150 170
1600 x 900	8	60 70 72 75 85 100 120 140 144 150
1600 x 1024	8	60 70 72 75 85 100 120
1600 x 1200	8	60 70 72 75 85 100 120
1680 x 1050	8	60
1920 x 1080	8	60
1920 x 1200	8	60 70 72 75 85 100
1920 x 1440	8	60 70 72 75 85
2048 x 1536	8	60

---

640 x 480	16	60 70 72 75 85 100 120 140 144 150 170 200 240
800 x 600	16	60 70 72 75 85 100 120 140 144 150 170 200 240
848 x 480	16	60 70 72 75 85 100 120 140 144 150 170 200 240
960 x 600	16	60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	16	60 70 72 75 85 100 120 140 144 150 170 200 240
1088 x 612	16	60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	16	60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	16	60

1280 x 768	16	60 70 72 75 85 100 120 140 144 150 170
1280 x 800	16	60 70 72 75 85 100 120 140 144 150 170
1280 x 960	16	60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	16	60 70 72 75 85 100 120 140 144 150 170
1360 x 768	16	60 70 72 75 85 100 120 140 144 150 170
1600 x 900	16	60 70 72 75 85 100 120 140 144 150
1600 x 1024	16	60 70 72 75 85 100 120
1600 x 1200	16	60 70 72 75 85 100 120
1680 x 1050	16	60
1920 x 1080	16	60
1920 x 1200	16	60 70 72 75 85 100
1920 x 1440	16	60 70 72 75 85
2048 x 1536	16	60

---

640 x 480	32	60 70 72 75 85 100 120 140 144 150 170 200 240
800 x 600	32	60 70 72 75 85 100 120 140 144 150 170 200 240
848 x 480	32	60 70 72 75 85 100 120 140 144 150 170 200 240
960 x 600	32	60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	32	60 70 72 75 85 100 120 140 144 150 170 200 240
1088 x 612	32	60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	32	60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	32	60
1280 x 768	32	60 70 72 75 85 100 120 140 144 150 170
1280 x 800	32	60 70 72 75 85 100 120 140 144 150 170
1280 x 960	32	60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	32	60 70 72 75 85 100 120 140 144 150 170
1360 x 768	32	60 70 72 75 85 100 120 140 144 150 170
1600 x 900	32	60 70 72 75 85 100 120 140 144 150
1600 x 1024	32	60 70 72 75 85 100 120
1600 x 1200	32	60 70 72 75 85 100 120
1680 x 1050	32	60
1920 x 1080	32	60
1920 x 1200	32	60 70 72 75 85 100
1920 x 1440	32	60 70 72 75 85
2048 x 1536	32	60

---

640 x 480	64	60 70 72 75 85 100 120 140 144 150 170 200 240
800 x 600	64	60 70 72 75 85 100 120 140 144 150 170 200 240
848 x 480	64	60 70 72 75 85 100 120 140 144 150 170 200 240

960 x 600	64	60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	64	60 70 72 75 85 100 120 140 144 150 170 200 240
1088 x 612	64	60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	64	60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	64	60
1280 x 768	64	60 70 72 75 85 100 120 140 144 150 170
1280 x 800	64	60 70 72 75 85 100 120 140 144 150 170
1280 x 960	64	60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	64	60 70 72 75 85 100 120 140 144 150 170
1360 x 768	64	60 70 72 75 85 100 120 140 144 150 170
1600 x 900	64	60 70 72 75 85 100 120 140 144 150
1600 x 1024	64	60 70 72 75 85 100 120
1600 x 1200	64	60 70 72 75 85 100 120
1680 x 1050	64	60
1920 x 1080	64	60
1920 x 1200	64	60 70 72 75 85 100
1920 x 1440	64	60 70 72 75 85
2048 x 1536	64	60

## Modes Supported by TV Encoders

---

Table A.3 and Table A.4 list the NTSC, PAL, and HDTV TV-Out modes supported by the NVIDIA driver.

**Table A.3** Mode Support for S-Video and Composite Out

Resolution	Bit depth	Comments
320x200	8, 16, 32	DirectDraw mode; not selectable as a Windows desktop
320x240	8, 16, 32	DirectDraw mode; not selectable as a Windows desktop
640x400	8, 16, 32	DirectDraw mode; not selectable as a Windows desktop
640x480	8, 16, 32	
720x480	8, 16, 32	Overscans (for video)
720x576	8, 16, 32	Overscans (for video)
800x600	8, 16, 32	
1024x768	8, 16, 32	Conexant 25871 only

**Table A.4** Mode Support for Component YPrPb Out and DVI Out

Resolution	Comments
480i (SDTV)	Supported on graphics boards with Conexant 875 or Philips 7108 TV encoders and compatible connectors, and compatible GeForce 6 Series and GeForce 7 Series GPUs.
480p (EDTV)	
720p (HDTV)	
1080i (HDTV)	
576i (PAL)	
576p (PAL)	

The driver supports manual overscan correction for component and DVI outputs. See the *ForceWare Graphics Driver User's Guide* for instructions on how to use the overscan correction features in the control panel.