



NVIDIA Quadro Professional Drivers ***Release 191 Notes***

Version 191.00

**For Windows 7 32-bit
and Windows 7 64-bit**

**NVIDIA Corporation
September 22, 2009**

Published by
NVIDIA Corporation
2701 San Tomas Expressway
Santa Clara, CA 95050

Notice

ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE.

Information furnished is believed to be accurate and reliable. However, NVIDIA Corporation assumes no responsibility for the consequences of use of such information or for any infringement of patents or other rights of third parties that may result from its use. No license is granted by implication or otherwise under any patent or patent rights of NVIDIA Corporation. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. NVIDIA Corporation products are not authorized for use as critical components in life support devices or systems without express written approval of NVIDIA Corporation.

Trademarks

NVIDIA, the NVIDIA logo, 3DFX, 3DFX INTERACTIVE, the 3dfx Logo, STB, STB Systems and Design, the STB Logo, the StarBox Logo, NVIDIA nForce, GeForce, NVIDIA Quadro, NVDVD, NVIDIA Personal Cinema, NVIDIA Soundstorm, Vanta, TNT2, TNT, RIVA, RIVA TNT, VOODOO, VOODOO GRAPHICS, WAVEBAY, Accuviv Antialiasing, the Audio & Nth Superscript Design Logo, CineFX, the Communications & Nth Superscript Design Logo, Detonator, Digital Vibrance Control, DualNet, FlowFX, ForceWare, GIGADUDE, Glide, GOFORCE, the Graphics & Nth Superscript Design Logo, Intellisample, M-BUFFER, nfiniteFX, NV, NVChess, nView, NVKeystone, NVOptimizer, NVPinball, NVRotate, NVSensor, NVSync, the Platform & Nth Superscript Design Logo, PowerMizer, Quincunx Antialiasing, Sceneshare, See What You've Been Missing, StreamThru, SuperStability, T-BUFFER, The Way It's Meant to be Played Logo, TwinBank, TwinView and the Video & Nth Superscript Design Logo are registered trademarks or trademarks of NVIDIA Corporation in the United States and/or other countries. Other company and product names may be trademarks or registered trademarks of the respective owners with which they are associated.

Intel, Indeo, and Pentium are registered trademarks of Intel Corporation. Microsoft, Windows, Windows NT, Windows Vista, Direct3D, DirectDraw, and DirectX are trademarks or registered trademarks of Microsoft Corporation. OpenGL is a registered trademark of Silicon Graphics Inc. PCI Express, PCI-SIG, and the PCI-SIG design marks are registered trademarks and/or service marks of PCI-SIG. DisplayPort is a trademark of the Video Electronics Standards Association (VESA).

Other company and product names may be trademarks or registered trademarks of the respective owners with which they are associated.

Copyright

© 2009 by NVIDIA Corporation. All rights reserved.



Table of Contents



1. Introduction to Release 191

Notes

Structure of the Document	1
Changes in this Edition	1

2. Release 191 Driver Changes

Version 191.00 Highlights	4
What's New in Release 191	4
What's New in Version 191.00	6
Limitations in This Release.	6
Special Instructional Notes for this Release	7
Changes in Version 191.00	9
Fixed Issues—Windows 7 (32-bit)	9
Fixed Issues—Windows 7 (64-bit)	9
Open Issues in Version 191.00	10
Not NVIDIA Issues	11
Unsupported Features	11
Feature Differences from Windows Vista	12
OpenGL Application Issues	13
Known Product Limitations	14
1280x1024 @ 60 Hz not Available on BenQ FP241W Monitors	14
Aero Must be Enabled for Windowed SLI AFR Mode Under Vista	14
SLI Connector Requirement on NVIDIA Quadro SLI Cards.	14
Image Sharpening Control not Available with GeForce 8 Series and later GPUs	14
Driver Reports 256 MB Memory on NVIDIA Quadro FX 330 Cards	15
Applying Workstation Application Profiles	15
Gigabyte GA-6BX Motherboard	15

3. The Release 191 Driver

Hardware and Software Support	17
Supported Operating Systems	17
Supported NVIDIA Products	18
Supported Languages	19
Driver Installation	20
Minimum Hard Disk Space	20
Before You Begin.	20
Installation Instructions.	20

A. Mode Support for Windows

General Mode Support Information	22
--	----

Default Modes Supported by GPU	23
Understanding the Mode Format	23
Quadro FX, CX, and NVS Series GPUs.	24
Modes Supported by TV Encoders.	26



List of Tables



Table 2.1	NVIDIA Control Panel Rotation Page Radio Buttons	12
Table 3.1	Supported NVIDIA Workstation Products	18
Table 3.2	Supported NVIDIA Quadro Blade/Embedded Graphics Board Series	19
Table A.1	Modes Supported for High Resolution Displays	22
Table A.2	Non-standard Modes Supported	22
Table A.3	Mode Support for S-Video and Composite Out	26
Table A.4	Mode Support for Component YPrPb Out and DVI Out	26

CHAPTER

1

INTRODUCTION TO *RELEASE 191 NOTES*

This edition of *Release 191 Notes* describes the Release 191 Quadro Professional Drivers for Microsoft® Windows® 7. NVIDIA provides these notes to describe performance improvements and bug fixes in each documented version of the driver.

Structure of the Document

This document is organized in the following sections:

- [“Release 190 Driver Changes” on page 3](#) gives a summary of changes, and fixed and open issues in this version.
- [“The Release 191 Driver” on page 17](#) describes the NVIDIA products and languages supported by this driver, the system requirements, and how to install the driver.
- [“Mode Support for Windows” on page 21](#) lists the default resolutions supported by the driver.

Changes in this Edition

This edition of the *Release 191 Notes* for Windows 7 includes information about NVIDIA graphics driver version 191.00, and lists changes made to the driver since version 186.30. These changes are discussed beginning with the chapter [“Release 191 Driver Changes” on page 3](#).

CHAPTER

2

RELEASE 191 DRIVER CHANGES

This chapter describes open issues for version 191.00, and resolved issues and driver enhancements for versions of the Release 191 driver up to version 191.00. The chapter contains these sections:

- “Version 191.00 Highlights” on page 4
- “Changes in Version 191.00” on page 9
- “Open Issues in Version 191.00” on page 10
- “Not NVIDIA Issues” on page 11
- “Known Product Limitations” on page 14

Version 191.00 Highlights

This section provides highlights of version 191.00 of the NVIDIA Release 191 Driver for Windows 7.

- [What's New in Release 191](#)
- [What's New in Version 191.00](#)
- [Limitations in This Release](#)
- [Special Instructional Notes for this Release](#)

What's New in Release 191

The section summarizes the following driver changes in Release 191:

- [NVIDIA Control Panel Updates](#)
- [Display Driver Updates](#)
- [CUDA Updates](#)
- [OpenGL Updates](#)

NVIDIA Control Panel Updates

Display Settings Pages

- The following pages have been revised to include TV settings controls:
 - **Adjust Desktop Color Settings**
Now includes controls to adjust TV color settings.
 - **Change Resolution**
Now includes controls to adjust TV and HDTV signal formats and resolution.
 - **Adjust Desktop Size and Position**
Now includes controls to adjust the TV screen size and position, and to resize the HDTV desktop.
- The following pages and links now appear in the Display category:
 - **HDCP Status** page
 - **Digital Audio** page
- After resizing the HDTV desktop, the new resolution created is now added to the list of available resolutions for that display, and also added to the resolution list within the game or application.

- The controls in the Manage Custom Resolutions page are now located in the **Change Resolution** page.

Video & Television Pages

- The following pages and controls have been moved to the Display category:
 - **Adjust Television Color Settings** page (see Display->Adjust Desktop Color Settings)
 - **Change the signal or HD format** page (see Display->Change Resolution)
 - **Select Digital color format** page (see Display->Change Resolution)
 - **Adjust screen size and position** page (see Display->Adjust Desktop Size and Position)
 - **Resize HDTV desktop** page (see Display->Adjust Desktop Size and Position)
 - **HDCP Status** page
 - **Digital Audio** page

3D Settings Pages

- **Preferred Refresh Rate** lets you override the refresh rate limitations imposed by the 3D application for the indicated monitor.
- **Power Management mode**

Many NVIDIA graphics cards support multiple performance levels so that the PC can save power when full graphics performance is not required. To provide more control over these power management capabilities, NVIDIA has added the Power Management Mode control. The control consists of two settings—*Adaptive* and *Prefer Maximum Performance*.

Adaptive: This is the default setting in which the graphics card monitors GPU usage and seamlessly switches between modes based on the performance demands of the application. This allows the GPU to always use the minimum amount of power required to run a given application, and can allow even older 3D games to run in lower power modes if the game does not require full 3D performance. NVIDIA recommends this setting for best overall balance of power and performance.

Prefer Maximum Performance: This setting lets you maintain the card at its maximum performance level when 3D applications are running regardless of GPU usage. This option can be set Globally (for all 3D applications), or an application profile can be created under Program Settings to set the preference for a particular 3D application.

This feature is supported only on select GeForce 9 Series and later GPUs and applies only to DirectX and OpenGL-based applications.

Workstation Pages

The **View system topology** page is now available with Windows 7 drivers.

Display Driver Updates

- Added support for hardware overlays on both Clone mode displays.
Previously, the driver supported only one hardware overlay, so only one Clone mode display could present the video overlay.

CUDA Updates

- Added support for 64-bit video encoding.
- Added support to make all GPUs within an SLI group available for CUDA applications to use.

OpenGL Updates

- Added support for OpenGL 3.1

What's New in Version 191.00

- See [“Changes in Version 191.00”](#) on page 9.

Limitations in This Release

The following are features that are not currently supported or have limited support in this driver release:

- **SDI**
This driver does not support the Serial Display Interface (a standard for driving high color depth displays).
- **Genlock/Frame Lock**
This driver does not support the ability to synchronize multiple display outputs with an external signal.
- **NVIDIA Control Panel Display Category**
The Graph tab on the Adjust Desktop Color Settings page is not available.
- **Workstation Category**
 - The **Synchronize Displays** page is not available with this driver version.
 - The **Send graphics to SDI output** page is not available with this driver version.
 - The **Manage Quadro Plex settings** page is not available with this driver version.

Special Instructional Notes for this Release

This section clarifies instructions for successfully accomplishing the following tasks:

Turning Off V-Sync to Boost Performance

To get the best benchmark and application performance measurements, turn V-Sync off as follows:

- 1 Open the NVIDIA Control Panel and make sure that *Advanced Settings* is selected from the control panel tool bar.
- 2 From the *Select a Task* pane, under 3D Settings, click **Manage 3D Settings**, then click the Global Settings tab.
- 3 From the Global presets pulldown menu, select **Base profile**.
- 4 From the Settings listbox, select **Vertical sync** and change its value to **Force off**, then click **Apply**.
- 5 From the Global presets pulldown menu, select **3D App - Default Global Settings** (the driver's default profile) or use the application profile that matches the application you are testing, then click **Apply**.

Be sure to close the NVIDIA Control Panel completely —leaving it open will affect benchmark and application performance.

NVIDIA Application Configuration Engine (ACE)

This driver includes the NVIDIA Application Configuration Engine (ACE), which automatically detects the workstation application and configures the appropriate profile settings in the NVIDIA Control Panel.

See the *NVIDIA Quadro Professional Drivers: NVIDIA Control Panel Quick Start Guide* for more information about this feature.

SLI Multi-OS – GPU Assignment in System Virtualization

On systems with two supported graphics cards installed, this driver supports a system virtualization tool's ability to directly assign a GPU to a guest virtual machine (VM). This direct assignment allows the host and guest VM to each run on their own operating system and with their own GPU and driver.

- **Supported Virtualization Software:** Parallels Workstation Extreme
- **Supported Graphics Cards**

Up to two different models can be used in a system, from among the following:

- Quadro FX 5800
 - Quadro FX 4800
 - Quadro FX 3800
- **Video BIOS Requirement**
 - The graphics card assigned to the guest VM needs video BIOS version 62.00.39.00.00 or later.

For a list of SLI Multi-OS certified workstations, virtualization software, and OS combinations, please see http://www.nvidia.com/object/sli_multi_os.html .

Changes in Version 191.00

The following sections list the changes made and issues resolved since driver version 190.38.

The NVIDIA bug number is provided for reference.

Fixed Issues–Windows 7 (32-bit)

Single GPU Resolved Issues

- Autodesk Maya–in the NVIDIA Control Panel there are two profiles with the same name for the application, whereas one of the profiles should be identified as the stereo version.
- Quadro FX 4600: SolidWorks 2009/2010–BOM table flyout window has garbage in the title bar.
- Quadro FX 1500: SolidWorks 2009/2010–the toolbox setup pages display Standards bitmaps only when moving the cursor over them, and not some of the icons.
- Quadro FX 3700: Catia V5–the application window blinks and refreshes incompletely when several frames are opened at the same time.

Fixed Issues–Windows 7 (64-bit)

Single GPU Resolved Issues

- Quadro FX 4600: SolidWorks 2009/2010–BOM table flyout window has garbage in the title bar.
- Quadro FX 1500: SolidWorks 2009/2010–the toolbox setup pages display Standards bitmaps only when moving the cursor over them, and not some of the icons.

Open Issues in Version 191.00

There are no open issues to report in version 191.00.

Not NVIDIA Issues

This section lists issues that are not due to the NVIDIA driver as well as features that are not meant to be supported by the NVIDIA driver for Windows 7.

- “Unsupported Features” on page 11
- “Feature Differences from Windows Vista” on page 12
- “OpenGL Application Issues” on page 13

Unsupported Features

The following are features and functionality that were available in driver releases supporting Windows XP, but are not—and will not be—available in driver releases for Windows 7:

- **High resolution scaling desktop (HRSD)**
- **MultiView Display Mode** (for NVIDIA Quadro NVS graphics cards)
- **NVKeystone**
- **Unified back buffer (UBB) controls**
- **OpenGL Video Overlays**

This is an operating system limitation.
- **Overclocking**

GPU overclocking is no longer supported in the default GPU driver control panel. This feature is available in the NVIDIA System Tools software, which you can download from NVIDIA.com.
- **GPU Temperature Monitoring**

Temperature monitoring is no longer supported in the default GPU driver control panel. This feature is available in the NVIDIA System Tools software, which you can download from NVIDIA.com.
- **AGP Settings Adjustment**
- **Video Zoom**
- **Pan & Scan** - the process of panning across the desktop in order to display a desktop on a monitor with lower resolution
- **Per-display Desktop Color Setting Adjustments**

For Clone mode, the desktop color setting adjustments through the NVIDIA Control Panel can only be made across all displays in a system, and not on a per-display basis.
- **Per-display Video Color Setting Adjustments**

For Dualview mode, the video color setting adjustments through the NVIDIA Control Panel can only be made across all displays in a system, and not on a per-display basis.
- **Edge Blending**

- **Run display optimization wizard**
- **Run multiple display wizard**
- **Run television setup wizard**
- **nView Horizontal and Vertical Span Modes**

Due to architectural changes in the new Windows Vista Window Display Driver Model (WDDM), span mode cannot be supported in NVIDIA graphics drivers. NVIDIA recommends using the built-in Windows Vista multi-display modes.

- **Display/Connection Wizard** (such as was provided with Windows Media Center Edition)
- **DVD/MPEG Extensions** (such as was provided with Windows Media Center Edition)
- **Audio Extensions** (such as was provided with Windows Media Center Edition)

Feature Differences from Windows Vista

Hotplug Action

Unlike the hotplug activity under Windows Vista, the default settings are not applied when a new display is hotplugged, and there is no message balloon alert stating that a new display was detected. Under Windows 7, all display connection and detection events are handled through the Windows 7 Connecting and Configuring Displays (CCD) mechanism.

NVIDIA Control Panel Rotate Display Page

The rotation radio button labels are changed slightly under Windows 7 to be consistent with the Microsoft panel:

Table 2.1 NVIDIA Control Panel Rotation Page Radio Buttons

Clockwise Rotation	Windows 7 Label	Windows Vista Label
0 degrees	Landscape	No rotation (Landscape)
90 degrees	Portrait	90 degrees to the right (Inverted Portrait)
180 degrees	Landscape (flipped)	180 degree rotation (Inverted landscape)
270 degrees	Portrait (flipped)	90 degrees to the left (Portrait)

OpenGL Application Issues

The following are known compatibility issues for OpenGL applications developed under Windows XP:

- Mixed GDI and OpenGL rendering does not work.

A number of applications use GDI to render UI components and object highlighting. This is not supported in the Windows Vista driver model.

NVIDIA recommends converting GDI rendering to OpenGL.

The following are some applications that are known to have this issue:

- Maya 7.01
- Applications, Tools, and Benchmarks not Supported Under Windows Vista
 - GLperf
 - 3ds max 8 (later releases may be supported)
 - CATIA V5R15 (V5R16 is supported)
 - PTC's CDRS 2001
- Front buffered rendering may be slow, especially when DWM is enabled.

Flushing the rendering queue while rendering to the front buffer may cause the window manager to recomposite. Applications should therefore minimize the frequency with which they flush the rendering queue.

Known Product Limitations

This section describes problems that will not be fixed. Usually, the source of the problem is beyond the control of NVIDIA. Following is the list of problems and where they are discussed in this document:

- “1280x1024 @ 60 Hz not Available on BenQ FP241W Monitors” on page 14
- “Aero Must be Enabled for Windowed SLI AFR Mode Under Vista” on page 14
- “SLI Connector Requirement on NVIDIA Quadro SLI Cards” on page 14
- “Image Sharpening Control not Available with GeForce 8 Series and later GPUs” on page 14
- “Driver Reports 256 MB Memory on NVIDIA Quadro FX 330 Cards” on page 15
- “Applying Workstation Application Profiles” on page 15
- “Gigabyte GA-6BX Motherboard” on page 15

1280x1024 @ 60 Hz not Available on BenQ FP241W Monitors

Even though the monitor EDID lists 1280x1024 @ 60 Hz, the screen turns blank when using an HDMI connection. This is an issue with the monitor and not the NVIDIA driver.

Because of this issue with the monitor, the NVIDIA driver blocks the problem mode (1280x1024 @ 60 Hz) and makes it unavailable.

Aero Must be Enabled for Windowed SLI AFR Mode Under Vista

Windows 7 Aero must be enabled in order to achieve SLI acceleration using windowed AFR mode.

SLI Connector Requirement on NVIDIA Quadro SLI Cards

The SLI connector that links two SLI cards is needed for proper SLI operation. However, the connector can be removed if you do not intend to enable SLI mode. If you remove the connector, then you must make sure that SLI mode is disabled from the NVIDIA control panel. Enabling SLI mode without the SLI connector installed will result in video corruption.

Image Sharpening Control not Available with GeForce 8 Series and later GPUs

With GeForce 8 Series and later graphics cards, the **Image sharpening** slider on the NVIDIA Control Panel-> Display->Adjust Desktop Color Settings page is grayed out.

This control is intentionally disabled because image sharpening is not supported on GeForce 8 series and later GPUs.

Driver Reports 256 MB Memory on NVIDIA Quadro FX 330 Cards

- **Problem**

When a 64 MB NVIDIA Quadro FX 330 card is installed, the driver reports that the card needs 256 MB, causing 256 MB of address space to be consumed.

- **Explanation**

This is not a bug but a product limitation.

The NVIDIA Quadro FX 330 GPU has some limitations that prevent the card from addressing less than 256 MB of system memory.

Applying Workstation Application Profiles

- **Background**

The workstation application profiles are software settings used by the NVIDIA Display Drivers to provide optimum performance when using a selected application. The profile also works around known application issues and bugs.

If there is an available setting for an application, it should be used, otherwise incorrect behavior or reduced performance is likely to occur.

- **Issues**

Configuration changes require that you restart the application.

Once an application is running, it does not receive notification of configuration changes. Therefore, if you change the configuration while the application is running, you must exit and restart the application for the configuration changes to take effect.

Gigabyte GA-6BX Motherboard

This motherboard uses a LinFinity regulator on the 3.3-V rail that is rated to only 5 A—less than the AGP specification, which requires 6 A. When diagnostics or applications are running, the temperature of the regulator rises, causing the voltage to the NVIDIA chip to drop as low as 2.2 V. Under these circumstances, the regulator cannot supply the current on the 3.3-V rail that the NVIDIA chip requires.

This problem does not occur when the graphics board has a switching regulator or when an external power supply is connected to the 3.3-V rail.

CHAPTER

3

THE RELEASE 191 DRIVER

This chapter covers the following main topics:

- “Hardware and Software Support” on page 17
- “Driver Installation” on page 20

Hardware and Software Support

Supported Operating Systems

The Release 185 driver, version 191.00, has been tested with Microsoft Windows® 7 RC build version 7100, and supports both 32-bit and 64-bit versions.

Supported NVIDIA Products

Table 3.1 and Table 3.2 lists the NVIDIA products supported by the Release 191 driver, version 191.00

Table 3.1 Supported NVIDIA Workstation Products

Product	Windows 7 32-bit	Windows 7 64-bit
NVIDIA Quadro FX 5800	X	X
NVIDIA Quadro FX 5600	X	X
NVIDIA Quadro FX 5500	X	X
NVIDIA Quadro FX 4800	X	X
NVIDIA Quadro FX 4700 X2	X	X
NVIDIA Quadro FX 4600	X	X
NVIDIA Quadro FX 4500 X2	X	X
NVIDIA Quadro FX 4500	X	X
NVIDIA Quadro FX 4400	X	X
NVIDIA Quadro FX 4400G	X	X
NVIDIA Quadro FX 4000	X	X
NVIDIA Quadro FX 3800	X	X
NVIDIA Quadro FX 3700	X	X
NVIDIA Quadro FX 3500	X	X
NVIDIA Quadro FX 3450	X	X
NVIDIA Quadro FX 3400	X	X
NVIDIA Quadro FX 1800	X	X
NVIDIA Quadro FX 1700	X	X
NVIDIA Quadro FX 1500	X	X
NVIDIA Quadro FX 1400	X	X
NVIDIA Quadro FX 580	X	X
NVIDIA Quadro FX 570	X	X
NVIDIA Quadro FX 560	X	X
NVIDIA Quadro FX 550	X	X
NVIDIA Quadro FX 540	X	X
NVIDIA Quadro FX 470	X	X
NVIDIA Quadro FX 380	X	X
NVIDIA Quadro FX 370	X	X
NVIDIA Quadro FX 370 low profile	X	X
NVIDIA Quadro FX 350	X	X
NVIDIA Quadro VX 200	X	X
NVIDIA Quadro CX	X	X
NVIDIA Quadro NVS 450	X	X
NVIDIA Quadro NVS 440	X	X
NVIDIA Quadro NVS 420	X	X
NVIDIA Quadro NVS 295	X	X

Table 3.1 Supported NVIDIA Workstation Products (continued)

Product	Windows 7 32-bit	Windows 7 64-bit
NVIDIA Quadro NVS 290	X	X
NVIDIA Quadro NVS 285	X	X

Table 3.2 Supported NVIDIA Quadro Blade/Embedded Graphics Board Series

Product	Windows Vista 32-bit	Windows Vista 64-bit
NVIDIA Quadro FX 3600M	X	X
NVIDIA Quadro FX 1600M	X	X
NVIDIA Quadro FX 770M	X	X
NVIDIA Quadro FX 560M	X	X
NVIDIA Quadro FX 370M	X	X
NVIDIA Quadro NVS 120M	X	X

Supported Languages

The Release 191 Quadro Professional Drivers supports the following languages in the main driver Control Panel:

English (USA)	German	Portuguese (Euro/Iberian)
English (UK)	Greek	Russian
Arabic	Hebrew	Slovak
Chinese (Simplified)	Hungarian	Slovenian
Chinese (Traditional)	Italian	Spanish
Czech	Japanese	Spanish (Latin America)
Danish	Korean	Swedish
Dutch	Norwegian	Thai
Finnish	Polish	Turkish
French	Portuguese (Brazil)	

Driver Installation

Minimum Hard Disk Space

The hard disk space requirement for 32-bit is minimum 105 MB for English-only, and 142 MB for International.

The hard disk space requirement for 64-bit is minimum 135 MB for English-only, and 170 MB for International.

Before You Begin

If you have previously installed NVIDIA nTune, NVIDIA recommends that you uninstall nTune before installing this driver. After the driver install is complete, you can reinstall NVIDIA nTune.

Installation Instructions

- 1 Follow the instructions on the NVIDIA .com Web site driver download page to locate the appropriate driver to download, based on your hardware and operating system.
- 2 Click the driver download link.
- 3 The license agreement dialog box appears.
- 4 Click **Accept** if you accept the terms of the agreement, then either open the file or save the file to your PC and open it later.
- 5 Extract the zip files to a temporary folder on your PC.
- 6 Open the NVIDIA driver installation .EXE file to launch the NVIDIA InstallShield Wizard.
- 7 Follow the instructions in the NVIDIA InstallShield Wizard to complete the installation.

APPENDIX



MODE SUPPORT FOR WINDOWS

This chapter details the Windows modes supported by the Release 191 driver for NVIDIA products. It contains these sections:

- “General Mode Support Information” on page 22
- “Default Modes Supported by GPU” on page 23
- “Modes Supported by TV Encoders” on page 26

General Mode Support Information

The NVIDIA graphics driver includes a standard list of display modes that are supported by default. These modes are listed in the section [“Default Modes Supported by GPU”](#) on page 23.

The actual modes available depend on the capabilities of the display. In addition, the NVIDIA graphics driver has a “dynamic EDID detection” capability and will make available *additional* modes that are listed in the display EDID, provided the graphics hardware can support it.

The NVIDIA graphics driver also supports the high resolutions available with the displays listed in [Table A.1](#) as well as the non-standard modes listed in [Table A.2](#).

Table A.1 Modes Supported for High Resolution Displays

Display	Maximum Resolution
Apple 30" Cinema HD Display (Dual link DVI)	2560x1600 @ 60 Hz
Dell WFP 3007 (Dual Link DVI)	2560x1600 @ 60 Hz
HP LP3065 dual-link DVI flat panel	2560x1600 @ 60Hz.

Table A.2 Non-standard Modes Supported

Resolution
1680 x 1050
1366 x 768

Default Modes Supported by GPU

This section lists the modes that are included by default in the driver INF for the following product families:

- “Quadro FX, CX, and NVS Series GPUs” on page 24

Understanding the Mode Format

Figure A.1 gives an example of how to read the mode information presented in this section.

Resolution	Color Depth	Refresh Rates
1024 x 768	32 60 70 72 75 85 100 120 140 144 150 170 200	

Example entry: 1024 x 768 32 60 70 72 75 85 100 120 140 144 150 170 200

Meaning:

Resolution:	1024 x 768
Color depth:	32 bpp
Refresh rates:	60 Hz, 70 Hz, 72 Hz, 75 Hz, 85 Hz, 100 Hz, 120 Hz, 140 Hz, 144 Hz, 150 Hz, 170 Hz, and 200 Hz

Figure A.1 Mode Format

Note:

- Horizontal spanning modes of 3840x1080 and above, and vertical spanning modes of 1920x2160 and above generally require at least 32 MB of video memory at 32 bpp.
- An “i” next to the refresh rate indicates an interlaced refresh rate.

Quadro FX, CX, and NVS Series GPUs

This sections lists the supported display resolutions, color depths, and refresh rates for the the products listed in [Table 3.1 on page 18](#) and [Table 3.2 on page 19](#) .

Standard Modes

640 x 480	8		60 70 72 75 85 100 120 140 144 150 170 200 240
720 x 480	8		60
720 x 576	8	50	
800 x 600	8		60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	8		60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	8		60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	8		60
1280 x 768	8		60 70 72 75 85 100 120 140 144 150 170
1280 x 800	8		60 70 72 75 85 100 120 140 144 150 170
1280 x 960	8		60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	8		60 70 72 75 85 100 120 140 144 150 170
1360 x 768	8		60 70 72 75 85 100 120 140 144 150 170
1600 x 900	8		60 70 72 75 85 100 120 140 144 150
1600 x 1024	8		60 70 72 75 85 100 120
1600 x 1200	8		60 70 72 75 85 100 120
1680 x 1050	8		60
1920 x 1080	8		60
1920 x 1200	8		60 70 72 75 85 100
1920 x 1440	8		60 70 72 75 85
2048 x 1536	8		60

640 x 480	16		60 70 72 75 85 100 120 140 144 150 170 200 240
720 x 480	16		60
720 x 576	16	50	
800 x 600	16		60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	16		60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	16		60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	16		60
1280 x 768	16		60 70 72 75 85 100 120 140 144 150 170
1280 x 800	16		60 70 72 75 85 100 120 140 144 150 170
1280 x 960	16		60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	16		60 70 72 75 85 100 120 140 144 150 170
1360 x 768	16		60 70 72 75 85 100 120 140 144 150 170

1600 x 900	16		60 70 72 75 85 100 120 140 144 150
1600 x 1024	16		60 70 72 75 85 100 120
1600 x 1200	16		60 70 72 75 85 100 120
1680 x 1050	16		60
1920 x 1080	16		60
1920 x 1200	16		60 70 72 75 85 100
1920 x 1440	16		60 70 72 75 85
2048 x 1536	16		60

640 x 480	32		60 70 72 75 85 100 120 140 144 150 170 200 240
720 x 480	32		60
720 x 576	32	50	
800 x 600	32		60 70 72 75 85 100 120 140 144 150 170 200 240
1024 x 768	32		60 70 72 75 85 100 120 140 144 150 170 200 240
1152 x 864	32		60 70 72 75 85 100 120 140 144 150 170 200
1280 x 720	32		60
1280 x 768	32		60 70 72 75 85 100 120 140 144 150 170
1280 x 800	32		60 70 72 75 85 100 120 140 144 150 170
1280 x 960	32		60 70 72 75 85 100 120 140 144 150 170
1280 x 1024	32		60 70 72 75 85 100 120 140 144 150 170
1360 x 768	32		60 70 72 75 85 100 120 140 144 150 170
1600 x 900	32		60 70 72 75 85 100 120 140 144 150
1600 x 1024	32		60 70 72 75 85 100 120
1600 x 1200	32		60 70 72 75 85 100 120
1680 x 1050	32		60
1920 x 1080	32		60
1920 x 1200	32		60 70 72 75 85 100
1920 x 1440	32		60 70 72 75 85
2048 x 1536	32		60

Modes Supported by TV Encoders

Table A.3 and Table A.4 list the NTSC, PAL, and HDTV TV-Out modes supported by the NVIDIA driver.

Table A.3 Mode Support for S-Video and Composite Out

Resolution	Bit depth	Comments
320x200	8, 16, 32	DirectDraw mode; not selectable as a Windows desktop
320x240	8, 16, 32	DirectDraw mode; not selectable as a Windows desktop
640x400	8, 16, 32	DirectDraw mode; not selectable as a Windows desktop
640x480	8, 16, 32	
720x480	8, 16, 32	Overscans (for video)
720x576	8, 16, 32	Overscans (for video)
800x600	8, 16, 32	
1024x768	8, 16, 32	Conexant 25871 only

Table A.4 Mode Support for Component YPrPb Out and DVI Out

Resolution	Comments
480i (SDTV)	Supported on graphics boards with Conexant 875 or Philips 7108 TV encoders and compatible connectors, and compatible GeForce 6 Series and GeForce 7 Series GPUs.
480p (EDTV)	
720p (HDTV)	
1080i (HDTV)	
576i (PAL)	
576p (PAL)	

The driver supports manual overscan correction for component and DVI outputs. See the *ForceWare Graphics Driver User's Guide* for instructions on how to use the overscan correction features in the control panel.